

LUMINAIRE, 250W HPS, 480V
COBRA STYLE

I. Quantity

The base bid shall include the indicated number of high pressure sodium (HPS) luminaires (250W) complete with internal regulator type ballast and 250 watt HPS lamps wired and erected as hereinafter specified.

II. Material

- a. Luminaire - The luminaire shall be suitable for attachment by means of a slipfitter connection to a 2" IPS bracket. The slip-fitter shall provide for adjustment of approximately 5 degrees above or below horizontal. Slip-fitter bolts shall be a minimum of 3/8" diameter. Slip-fitter shall be totally enclosed in luminaire housing.

Each luminaire shall be furnished with a mounted 480 volt ballast. The ballast shall be a CWI, regulated type, with three windings and isolation between the two secondary windings and primary winding. The ballast must provide a maximum of 25% wattage variation (measured along the left side of the lamp trapezoid) to a normal lamp when nominal input voltage varies within a range of + or - 10%. Each luminaire shall be prewired with two (2) metal oxide varistors to limit surge voltages on equipment by diverting surge currents to ground. Each metal oxide device shall be installed between incoming leads and fixture ground. The varistors shall comply with the ANSI-IEEE standard C62.11-1987 and shall be capable of operation in an outdoor environment with a temperature range of -40 degrees C to 40 degrees C. The metal oxide shall have the following electrical ratings and characteristics:

1. Rating of 650 volts rms with MCOV of 540 volts rms.
2. An 8/20 micro seconds current wave of 5 KA shall have a maximum discharge voltage of 2.7 KV crest.
3. Duty cycle of 1.5 KA crest. High current short duration (HCSD) of 10 KA crest.

The starting circuit must provide a minimum starting pulse repetition rate of one pulse per cycle (symmetrical). The spike position must occur within a minimum of + or - 20 degrees of the center of the open-circuit voltage waveform. The pulse peak voltage should be a maximum of 3000 volts. Pulses must be provided in the same polarity as the open circuit voltage.

MIS-33
10/01

The starting circuit and ballast must be capable of starting and maintaining lamp burning in ambient temperatures as low as -20 degrees Fahrenheit. Ballast, starting circuit, and lamp shall be pre-wired and ready for installation; all of which shall be readily accessible for maintenance purposes. Each luminaire starting circuit and ballast shall be factory tested and matched to assure proper component tolerances and pulse parameters.

Each luminaire shall consist of a die cast aluminum alloy housing forming the upper half of the assembly, a separate reflector, and heat resisting glass reflector mounted in a hinged holding ring. The lamp socket shall be factory set for Type III. The assembly shall be drip proof and bug proof. The entire unit shall be prewired and ready for installation. The nominal lamp voltage shall be 100 volts. The luminaire shall be an approved equal in appearance, quality and design to Thomas and Betts #U-1150072 or Cooper #OVZ25SC83EU1383.

- b. Lamps - The High Pressure Sodium lamps to be furnished with the luminaire shall be 250 watt, with a rated life of 24,000 hours equal in quality, design and performance to General Electric Company's LU250.

III. Installation

The luminaire shall be installed on the bracket as shown on the drawings and indicated in the field by the engineer. Orientation and leveling of the units shall be so as to provide for uniform appearance, maximum lighting efficiency and ease of maintenance.

IV. Information Required

Bidders shall also furnish complete performance data on the luminaires equipped with the lamp they propose to furnish. The data submitted shall contain at least the following information:

- Isocandle Curves from Photometric Test
- Utilization Curves
- Isolux Lines of Horizontal Foot-candles from a single unit
- Total Wattage of Fixture

V. Quotation

The complete 250 Watt High Pressure Sodium Luminaire with lamp shall be quoted as a unit price in the appropriate place of this document.